



PUSH STATIONS

SERIES NPS

Description:

Multipurpose push stations for manual activation of SAFEPATH® and SAFEPATH®4 Voice Evacuation Systems prerecorded messages. Can be used to manually activate a message in the event of an emergency or for alerting.

Features:

- UL S7255 Listed switch assembly
- Available in five colors: Red, Green, Yellow, White, or Blue
- Custom wording available
- Polycarbonate faceplate
- Stainless steel backplate
- ADA Compliant
- Mounts to single gang electrical box
- Interchangeable or replaceable Normally Open (NO) and Normally Closed (NC) Single Pole, Single Throw gold plated contact blocks rated for 3 amps @ 600 VAC or 1 amp @ 250 VDC
- Can be reset by depressing the “Push” button, and turning clockwise a ¼ turn
- Comes with one (NO) contact and one (NC) contact
- Measurements: 5” H x 3¼” W x 1½” D



Applications:

- For use with SAFEPATH® and SAFEPATH®4 Voice Evacuation Systems
- Manual activation of messages in the event of an emergency
- Manual activation of messages to alert or warn others

Architects and Engineers Specifications

Push stations shall be designed for manual activation of SAFEPATH® and SAFEPATH®4 Voice Evacuation Systems prerecorded messages. The faceplate shall be constructed of polycarbonate. The backplate shall be stainless steel. The switch assembly shall be a UL Standard S7255 listed Normally Open (NO) and Normally Closed (NC) Single Pole, Single Throw gold plated contact blocks rated for 3 amps @ 600 VAC or 1 amp @ 250 VDC. The push stations shall be ADA compliant. The push stations shall mount to a single gang electrical box. The push station shall be capable of being reset by depressing the "Push" button, and turning clockwise a ¼ turn. The push stations shall be available in five colors: red, green, yellow, white or blue. Custom word printing on the top of the push station shall be available.

Ordering Information

Model Number	Order Code	Color	Description
NPS-R	9767	Red	Push Station for manual message activation
NPS-G	9768	Green	
NPS-Y	9769	Yellow	
NPS-W	9770	White	
NPS-B	9771	Blue	
NPS-NO	0523		Push Station Normally Open Contact
NPS-NC	0524		Push Station Normally Closed Contact

Wording	Model Code Suffix	Wording	Model Code Suffix
Land Attack	-001	Emergencia	-026
Sea Attack	-002	Alarm Yellow	-027
Colors	-003	Delta	-028
Low Threat	-004	Alarm Red	-029
Medium Threat	-005	Withdrawel	-030
High Threat	-006	Emergency	-031
Small Craft	-007	Audio Test	-032
Unknown Object	-008	All Clear	-033
Code Bravo	-009	Fire Test	-034
Low	-010	Evac Drill	-035
Medium	-011	Weather	-036
High	-012	Chem-Bio	-037
Water Attack	-013	Suspicious	-038
Chemical Spill	-014	Fire*	-039
Gas Release	-015	All	-040
Evacuation	-016	Bomb	-041
Help	-017	Test	-042
Assistance	-018	Area	-043
Severe Weather	-019	Bomb Threat	-044
Tornado	-020	Terrorist Threat	-045
Medical Alert	-021	Toxic Chemical	-046
Power Shut Down	-022	Disaster	-047
Blank / No Wording	-023		
Strobe	-024		
Alert	-025		

Wording Matrix for top of the Push Station

Any "wording suffix" can be printed on any color push station.

Examples:

9767-003 NPS-R-003 Red Push Station, Colors
 9771-010 NPS-B-010 Blue Push Station, Low

Note: Custom wording is available, please contact customer service.

*For non UL Life Safety Applications

**WE ENCOURAGE AND SUPPORT NICET CERTIFICATION
 3 YEAR WARRANTY**

Made in USA



Distributed By:

National Sales Office
 800-631-2148
 Canada 800-397-5777
 E-Mail: Info@wheelockinc.com
<http://www.wheelockinc.com>